

Div. :	Descrizione - Tipologia Apparati o servizi	Data / rev.	Usò
Area Tecnica	Manuale configurazione - DrayTek Vigor160 Series	16-11-2020 / 01	Pubblico

# DrayTek Vigor 160 Series

Di seguito è riportato un esempio di come configurare l'interfaccia WAN del Modem VIGOR 160 Draytek per il servizio Internet FIBRA FTTC/VDSL con le credenziali fornite da TECHLABITALIA.

## 01 GENERAL SETUP

Selezionato il menù General Setup, selezionare l'interfaccia WAN1 per inserire i parametri di collegamento:



- selezionare come Physical Mode: **VDSL2**
- Inserire nel campo Tag value, sotto la voce VLAN Tag insertion (VDSL2), il valore **835**

### Esempio



WAN >> General Setup

WAN 1

Enable:  Yes  No

Display Name:

Physical Mode:

DSL Mode:

Physical Type:

DSL Modem Code:

VLAN Tag insertion (ADSL):

Tag value:  (0~4095)

Priority:  (0~7)

VLAN Tag insertion (VDSL2):

Tag value:  (0~4095)

Priority:  (0~7)

Active Mode:

Note:

1. The line speed setting of WAN interface is available only when According to Line Speed is selected as the Load Balance Mode.
2. In DSL auto mode, the router will reboot automatically while switching between VDSL2 and ADSL lines.

## 02 INTERNET ACCESS

Entrare nella voce di menu **WAN > Internet Access** e posizionarsi sull'interfaccia WAN1 per effettuare le seguenti operazioni:

- selezionare la tab **PPPoE/PPPoA**;
- cliccare sul tasto **Details Page** per inserire i parametri forniti nella lettera di attivazione.

WAN >> Internet Access

WAN 1

PPPoE / PPPoA

Enable  Disable

Modem Settings (for ADSL only)

Multi-PVC channel:

VPI:

VCI:

Encapsulating Type:

Protocol:

Modulation:

PPPoE Pass-through

For Wired LAN<sup>2</sup>

WAN Connection Detection

Mode:

MTU:  (Max:1500)

Path MTU Discovery:

ISP Access Setup

Service Name<sup>1</sup>:

Username:

Password:

Separate Account for ADSL

PPP Authentication:

IP Address From ISP:

Fixed IP:  Yes  No (Dynamic IP)

Fixed IP Address:

Default MAC Address

Specify a MAC Address

MAC Address:

Index(1-15) in Schedule Setup:

=>

Note:

- 1: (Optional) Required for some ISPs. Leave blank if in doubt because the connection request might be denied if "Service Name" is incorrect.
- 2: If this box is checked while using the PPPoA protocol, the router will behave like a modem which only serves the PPPoE client on the LAN.

Selezionato il menù Physical Connection è possibile verificare se il modem è correttamente allineato.