

Div. :	Descrizione - Tipologia Apparatati o servizi	Data / rev.	Uso
Area Tecnica	Manuale configurazione - Linksys AM200	11-07-2011 / 01	Pubblico

## Linksys AM200

1. Collegare l'alimentatore fornito in dotazione con il modem alla presa di corrente. Sul retro del dispositivo, collegare il cavo di rete fornito al modem e al computer.
2. Accendere l'interruttore. In questa fase il dispositivo "esegue un reset" della durata di circa 5 secondi, ovvero tutti i led sul pannello frontale lampeggiano. Al termine si illuminano i led POWER.
3. Collegare il cavo della linea ADSL sul retro e alla presa telefonica e attendere circa 15 secondi. Il led ADSL inizia a lampeggiare e diventare fisso dopo alcuni secondi.

**a) Aprire il browser** (*Internet Explorer, Mozilla Firefox, Google Chrome, Safari, Opera*) ed inserire l'indirizzo IP di default **192.168.1.1**



**b) Alla richiesta di autenticazione** inserire:

- Nome utente: **admin**
- Password: **admin**

A questo punto verrà visualizzata la schermata del setup di base del dispositivo.

The screenshot shows the Linksys AM200 web interface. The main navigation bar includes 'Setup', 'Security', 'Applications & Gaming', 'Administration', and 'Status'. Under 'Setup', there are sub-tabs for 'Basic Setup', 'Config', and 'Advanced Routing'. The 'Basic Setup' page is active, showing the following configuration options:

- Encapsulation:** RFC 2364 PPPoA
- Virtual Circuit ID:** VPI (Range 0 - 255) and VCI (Range 0 - 65535)
- Multiplexing:** LLC and VC (selected)
- DSL Modulation:** Auto
- PPPoA Settings:**
  - User Name: [ ]
  - Password: [ ]
  - Keep Alive:  (Redial Period 0 Min. (Range 0-500))
  - Connect on Demand:  (Max Idle 20 Min. (Range 1-1000))
- Optional Settings (required by some ISPs):**
  - Host Name: [ ]
  - Domain Name: [ ]

On the right side, there is a 'Basic Setup' sidebar with instructions: 'ADSL Settings: The values for this section must match those of your ADSL Internet connection. Please check with your Internet Service Provider to verify the correct settings.' and 'PPPoA Settings: Please enter the PPPoA username and password that was provided by your Internet Service Provider.'

**c) Inserire i seguenti parametri:**

- Nel campo *Encapsulation* selezionare la voce relativa al protocollo **PPPoA**
- VPI: **10**
- VCI: **35**
- Multiplexing: **VC**
- DSL Modulation: **AUTO**
- **User Name** e **Password** forniti da TechlabItalia
- Abilitare **KeepAlive**

**FINE**